



DIGITAL EVENT COUNTER

COMMON SPECIFICATIONS



DEC - 500



DEC - 501



DEC - 502

Display	: 6 Digit 0.5" ht 7 segment LED for DEC-500 / 502 6 Digit 0.3" ht 7 segment LED for DEC-501
Range	: 1 to 999999 Counts
Count Input	: a) Proximity Switches (PNP / NPN) b) Potential free contacts c) 5 to 30 V. DC. Voltage pulse. d) 230 V.AC. Mains pulse (Optional)
Counting Speed	: 0 to 3 / 30 / 100 / 1000 / 2500 Hz (Programmable)
Sensor Supply	: 12 V.DC. 30 mA max.
Control Input	: Hold (Optional)
Reset	: Front Reset / Remote Reset (Programmable)
Memory Retention	: Non Volatile (E ² prom) upto 10 years
Operating Temp	: 0 to 55 °C
Relative Humidity	: Below 95% RH (Non condensing)
Supply	: 90 V to 270 V. AC., 50 / 60 Hz

Dimensions (H x W x D) mm	48 x 96 x 120	72 x 72 x 110	96 x 96 x 120
Panel Cutout (H x W) mm	46 x 92	68 x 68	92 x 92

ORDERING CODE :

DEC - XXX	
XXX	SIZE
500	48 X 96 mm
501	72 X 72 mm
502	96 X 96 mm



Manufacturers:

SHRIJI ELECTRONICS

7, Shivsagar Society, Krishna Nagar, Andheri Kurla Road,
Safed Pool, Pipe Line, Mumbai-400072.

Tel. : 022 2851 0847, 2851 1036. 2852 0149

Email : shriji_ele@mtnl.net.in www.shrijielectronics.com

